

1. Run NovaLCT-Pluto, move the cursor over the *Advanced Login (A)* and click the button.

🛐 NovaLCT	-Pluto V4.5.2								_	×
System(S)	Setting(N) To	ols(C) Use	r(U) Plug-ir	n Tool(P) La	anguage(Lang)	(L) Help(H)				
Brightness	Display Control	Monitor	Advanced L	ogin(A) d Main Boa	ard Power					
Remote Syste	m Info									
Remote Addr	ess: PSD100	-J-11 (169.25	4.238.5)	Net Cor	nection:	Connected	Device Count:	1	Search	
Monitor Info										
		111		\bigcirc	8	×		***		
				۲		•		٠		
					·				, ,	
Connection Sta	tus: Connected c	ontrol card								:

2. Login with the password "admin".

S NovaLCT-Pluto V4.5.2						_		\times
System(S) Setting(N) Tools(C) User	(U) Plug-in Tool(P)	Language(Lang)(L)	Help(H)					
Brightness Display Control Monitor	User Login	• 1	×					
Remote System Info Remote Address: PSD100-J-11 (169.254	Password:	admin 		ice Count:	1	<u>Q</u> 50	arch	
Monitor Info	Login	Cance	d	31			•	
	• •		•	•	•			
Connection Status: Connected control card								.:

3. Click on the *Function Card* button.

S NovaLCT-Pluto V4.5.2				- 🗆	\times
System(S) Setting(N) Tools(C) U	ser(U) Plug-in Tool(P) Langua	ge(Lang)(<u>L</u>) Help(<u>H</u>)			
Screen Config	Display Control Monitor	Junction Card Main Boar	rd Power		
Remote System Info					
Remote Address: PSD100-J-11 (169.	254.238.5) Net Connectio	n: Connected	Device Count: 1	Search	
Monitor Info					
	i 🌍 i	8 5	[]]		
			•		
<u> </u>					



4. Click on the *Refresh* and find the function card.

Function Card Management		×
Refresh	Power Management Monitor Data External Device Load Program	

5. Click to select the *Load Program*.

Function Card Managemer

Function Card Management		×
Refresh	Power Management Monitor Data External Device Function Card Information Model ID: FPGA Version:	Refresh



6. Type password "admin" on this page and select new program, then click change icon , and click refresh button to check program version.

Function Card Management		\times
Function Card Management	Power Management Monitor Data External Device Load Program Function Card Information Model ID: 81 01 FPGA Version: 04 04 00 00 FPGA Version: 04 04 00 00 FPGA Note: 2015.12.23 FuncCardF600 V4.4.0.0 STD Refresh Image: Constraint of the selected function card for all function card Exit Select Program FunctionCardData-F600 Program Name: FunctionCardData-F600 Program Path: H*Data_FuncCard V4.4.0.0	×
Save FPGA program:Succeed! Function Card Management Refresh 	2016/8/26 10:39:42COM1:Save FPGA program:Succeed 2016/8/26 10:39:52Read FPGA program version of function card:Succeed 2016/8/26 10:39:52Load program succeed 2016/8/26 10:39:52Load program succeed V Power Management Monitor Data External Device Function Card Information Model D: \$1 01	×
	FPGA Version: 04 04 00 00 FPGA Note: 2015.12.23 FuncCardF600 V4.4.0.0 STD Load program for selected function Load program for all function card Exit Select Program Program Name: Program Version: Program Path: Change 	
	2016/8/26 10:38:21Read Model ID of function card: Succeed	